



EU20i

The EU20i uses Honda's advanced four-stroke GX100 engine for a maximum power output of 2,000 watts AC, and rated output of 1,600 watts.

INTRODUCTION

EU20i GENERATOR

The EU20i starts first time every time with Honda's reliable one pull easy start system. It features a microcomputer-controlled sinewave inverter that guarantees commercial-quality electricity – making it ideal for use with frequency-sensitive electrical equipment such as laptops/tablets.

It's environmentally friendly with low emissions, less noise and low fuel consumption than its two-stroke counterparts, and can run up to 8* hours of continuous operation on a full fuel tank. Lightweight (21kg) and whisper-quiet (from 53dB(A)), the EU20i was the flagship generator of not just Honda, but the portable power industry until the release of the EU22i Generator.

The EU20i is backed by Honda's extensive 4 year Domestic warranty.

*With eco-throttle switched on at 1/4 output.

UPGRADE TO THE EU22i

The world's best-selling leisure generator, the EU20i just got a whole lot better! With the release of the EU22i, with 200W MORE power, the all-new Honda EU22i Generator can power more than ever before. Used for leisure, back-up power and for the job site, it really packs a punch! Check out the NEW EU22i Generator

Limited stock of the EU20i Generator is available in selected Honda Power Equipment dealerships.

SPECS

ENGINE

ENGINE	GX100
DISPLACEMENT	98 (cc)
IGNITION SYSTEM	Transistor
OIL ALERT	Yes
STARTING SYSTEM	Recoil
STOPPING SYSTEM	Ignition primary circuit ground
RECOMMENDED FUEL	Unleaded
FUEL (APPROX)	0.64 (litres/hr)
FUEL TANK CAPACITY (LITRES)	4.1
CONTINUOUS OPERATING HOURS	8hr*/4hr
OPERATING NOISE LEVEL (AT 7M)	53dB(A)*/59dB(A)

DIMENSIONS

DIMENSIONS (LXWXH)	510 x 290 x 425 (mm)
DRY WEIGHT (KG)	21 kg

FEATURES

MAXIMUM AC OUTPUT	2000VA
RATED AC OUTPUT	1600VA

DC OUTPUT (GENERATOR/CHARGER)	12V-8.3A
BATTERY CHARGING	Yes
FREQUENCY METER	No
VOLT METER	No
GENERATOR TYPE	Multipole field rotation type (inverter)
RATED VOLTAGE	240 (V)
RATED FREQUENCY	50 (Hz)
FUEL GAUGE	No
AC CIRCUIT BREAKER	Yes
DC CIRCUIT BREAKER	Yes
AUTO THROTTLE	Eco-throttle
AUTO CHOKE	No
LARGE CAPACITY AIR CLEANER	Yes
LARGE CAPACITY FUEL TANK	Yes
LARGE CAPACITY MUFFLER	Yes
PILOT LAMP	Yes
AIR CLEANER	Dual element type
PARALLEL OPERATIONS CONNECTION PORTS	Yes

**PARALLEL OPERATIONS
CONNECTION CABLE**

Optional

4 WHEEL DOLLY KIT

No

CONDITION

*With eco-throttle switched on at 1/4 output

RRP

Limited stock available in selected store.

VISIT HONDA POWER EQUIPMENT WEBSITE

For terms and conditions please visit [http://about.hondampe.com.au/Terms and Conditions](http://about.hondampe.com.au/Terms_and_Conditions)

The information in this document is valid as of 16/05/2018. For the most up to date information please visit <http://powerequipment.honda.com.au>